




# Bluetooth MESH(SIG) Gateway User Manual



## Product Description

Bluetooth MESH (SIG) gateway is composed of highly integrated wireless WIFI module, Low energy wireless bluetooth module and main board. Through the Tuya Smart APP, users can implement device addition, device reset, third-party control, and Bluetooth (single point & mesh) group control to meet smart home and other applications.


## Specifications

| Physical features    |                            |
|----------------------|----------------------------|
| Size                 | 65*65*14.5mm               |
| Net weight           | 29g                        |
| Status LED indicator | 2 LED                      |
| Button               | 1 (reset)                  |
| Power                | Micro USB DC5V             |
| Working current      | <1A                        |
| Adaptor output       | 5V 1A                      |
| Working temperature  | -10~55°C                   |
| Working humidity     | 10%~90%RH (non-condensing) |
| Storage temperature  | -20~60°C                   |
| Storage humidity     | 5%~90%RH (non-condensing)  |
| Hardware interface   | 1 Micro-USB                |

| Wireless technology | WIFI 802.11 b/g/n                                |  |
|---------------------|--|--|
|                     | Bluetooth single point & Mesh                    |  |
| Antenna type        | Built-in onboard antenna                         |  |
| RF characteristics  |  |  |
|                     | WIFI   | Bluetooth single point&Mesh  |
| Wireless frequency  | 2,400 -2,4835GHz                                 | 2,400-2,4835 GHz   |
| Network standard    | WIFI 802.11 b/g/n                                | Bluetooth single point& Mesh   |
| Transmission power  | 21dBm  | 7dBm   |
| Channel             | CH1-CH11   | CH0-CH9 channel<br>2402MHz;2404MHz;<br>2406MHz;2408MHz;<br>2410MHz;2480MHz<br>one channel is added every 2MHz. |
| Transmission speed  | 11b:1,2,5.5,11 (Mbps)                            | 1Mbps (BLE 4.2)  |
|                     | 11g:6,9,12,18,24,36,48,54(Mbps)                  | 2Mbps (BLE5.0)   |
|                     | 11n:HT20 MCS0-7<br>11n:HT40 MCS0-7               |  |
| Network performance |  |  |
| Wireless encryption | AES 128bit encryption                            |  |
|                     | WPA-PSK/WPA2-PSK,<br>WPA/WPA2 security Mechanism |  |
|                     | long distance App configuration                  |  |
| Network management  | WIFI module firmware upgrade                     |  |
|                     | bluetooth module firmware upgrade                |  |

## Packing list

- Bluetooth MESH (SIG) gateway x1
- Power cable x1
- User manual x1



1

2

3

4


## Status indicator and reset

### Blue: bluetooth status

- Flashing means to be connected and allowed to connect to the network
- keep "on" for a long time, which means device is activated
- keep "off" for a long time, which means device is not activated

**Reset method:** Press and hold the button for 5 seconds and see the blue indicator flashing several times, which means the reset is successful.

- Select 2.4GHz Wi-Fi network and enter password. Please confirm the blue indication is flashing for normal pairing.
- The connection will take about 30-120 seconds, depending on your network condition
- Once the device has been added successfully, you will be able to find the device on "My Home" page



210907

5

6

7

8



9

10

11

12