



4*XHP50.2

USER MANUAL

Safety precautions

- Use only reputable 18650 cells of known origin. Quality high drain cells (over 20A), from Samsung Sony are recommended.
- Cells are used in parallel, make sure all cells are identical: same make, model, capacity, age, used cycles, and furthermore charged to the same level.
- When the battery voltage is too low, please charge it in time. The flashlight has a low battery prompt (when the voltage is lower than 2.8V, the flashlight will enter the protection function and turn off the flashlight).
- Do not shoot directly into the eyes of people or animals, and do not irradiate moving vehicles or flammable objects. It is normal for the head to heat up quickly, please use it with caution to prevent hot hands.
- Unscrew the battery tube and insert the three 18650 cells. Note that the Lamp require button-top type cells. Take care to observe the correct polarity for each cell.
- Double check the polarity every time before closing: The lower seated batteries must point with plus (nipple) towards the head. The higher ones must look with plus to the open back! All flat ends look at the springs. Screw the battery tube back. The HK05 will flash once when electrical contact is made. Continue to tighten the battery tube to a gentle stop. Do not overtighten.
- There is a very small drain on the battery while OFF. This should not be of any concern, but we recommend removing the cells (or partially loosening the tail-cap) if the HK05 will not be used for several months.
- Safety use reminder: The product is a strong light and high-power flashlight. When the battery is fully charged, it will be turned on for about 45 seconds and it will downshift. The head will quickly heat up. In a hot environment, the flashlight can easily exceed 55 degrees. Anti-scalding, warm reminder. .

Basic Parameters

Emitter	Flux	Range	Candela
XHP50.2	15000 LM	750M	14WCD

Specifications

Body : 6063 aluminum alloy material with type III hard-coat anodizing.

Lens: Double-side AR coated toughened glass lens 98% light transmission.

Color : Black/desert yellow

Battery: Three button-top 18650 cells.

Springs: Silver plated copper alloy with low low internal resistance

charging display: Type-C bidirectional fast charging port available. The indicator light of the switch is red when charging and it changes to blue when fully charged.

charging time: Three 3000MA 18650 cells take about 3 hours to fully charge

LED: four LEDs XHP50.2 Highest level of bright light

Emitter: 6000-6500K

Ingress rating: Normal waterproof not diving

Dimension: 140mm (length) x56mm(head)x50mm (tail)x46mm at the handle

Weight:: N.W375g G.W700g

Packing list:

- HK04 Flashlight *1
- O ring *1
- Product Instruction *1
- carrying strap*1
- Type-C USB pallet *1
- C-C *1

Quick Start

Ramping: Infinitely Dimmable: When off, press and hold the switch to infinitely dim up the brightness, release the switch and press again to change the dimming direction and lower the brightness.

Extremely bright: Double-click quickly in any mode to enter extremely bright, when the temperature of the flashlight reaches 55°C, there will be a temperature control protection function, the brightness will slowly drop to 3500 lumens, and continue to be on for a long time (about 180 minutes). bright gear.

Strobes: When turned on, double-click - extremely bright and double-click again to enter the burst - double-click again to enter the SOS mode - double-click again to enter the tactical flashing, click any gear to close

Power display: Battery level indicator: when the battery is below 3.2V blue light flashes, below 3V red light flashes, below 2.8 will automatically shut down
charging power: Charging 5V 3A, 9V 2A, Huawei SCP5V 4.5A, two-way fast charging.

Ramping/Stepped Ramping Switch: 3 Clicks to enter Ramping and Stepped Ramping Switch while the light is ON.

Stall mode: first 100 lumens, second 1000 lumens, third 3500 lumens, fourth 5000 lumens, double click to very bright 15000 lumens, double click again to enter burst flash.

LockoutMode: Press and hold for three seconds to enter the lock function when switched off, and for three seconds to unlock when switched on.



We wish you a lot of fun with this light!



Haikelite Web: <http://haikelite.top>

Haikelite : <https://Haikelite.es.aliexpress.com>

Welcome to our website, we will be happy to serve you. There are more interesting and exciting flashlights for your choosing.