

User Manual

FPV Goggles

VR005





Main function



No.	Name	Function
ባ	Power switch	Long press to start when when in shutdownLong press to power off when in boot state.
S	Menu/ Automati	•Click button "S" to bring up Setting menu, and then click again to go to next menu.
	cally	• Long press to search channel automatically



		•Click button "B" to switch bands between
В	Bands	"A,B, C, D, E, F" when in 5.8G mode
		• Used as "-" when in Setting menu
		•Click button "CH" to switch channel between
СН	Channel	"1,28" when in 5.8G mode
		• Used as "+" when in Setting menu
USB	USB	• For charging (DC 5V power)

Operation

1. S Channel auto-searching

Click button "S", the device will search the signal according to the 48 channel one by one, and will stop once get the video signal. If the video signal is not you want to get, please click this button again to continue search.

2. B Bands

Click to this button continuously to switch bands between the six bands "A, B, C, D, E, F" when search channels manually.

4. CH Channel

When search channels manually, and after bands settled, click this button continuously to switch the 8 channels one by one in settled



band.

Product Specification

Screen Size: 2.7 inches,

Resolution: 960*240 pix

Brightness : 300cd / m2 of high brightness, for outdoor use

Field of view: 0/120 degrees (horizontal / vertical)

Magnification: 3.5x

Distortion: No distortion

Material: PMMA

Transparency: > 98%

Power consumption: 1.4W

RX: Built-in 48CH 5.8G Hz

Working temperature: -10°C-60°C

Storage temperature: -20°C-90°C

Product weight: 145 g

Product size: 150mmX120mmX60mm



48 Channels as following:

- Band A: 5645, 5665, 5685, 5705, 5885, 5905, 5925, 5945
- Band B: 5740, 5760, 5780, 5800, 5820, 5840, 5860, 5880
- Band C: 5725, 5745, 5765, 5785, 5805, 5825, 5845, 5865
- Band D: 5733, 5752, 5771, 5790, 5809, 5828, 5847, 5866
- Band E: 5658, 5695, 5732, 5769, 5806, 5843, 5880, 5917
- Band F: 5362, 5399, 5436, 5473, 5510, 5547, 5584, 5621